

# EG6500C



- 1 Economical, portable power with traditional Honda durability and performance
- 1 6,500 watts maximum AC output
- 1 Home stand-by and Commercial usage (for non-GFCI applications)
- 1 Suitable for rental applications



## SPECIFICATIONS

<b>GENERATOR TYPE</b>	BRUSH TYPE	<b>TRANSPORT WHEELS</b>	OPT. (P/N 06710-Z22-A40ZA)
<b>MAXIMUM AC OUTPUT (WATTS)</b>	6500	<b>LIFTING HOOK</b>	OPT. (P/N 06810-Z22-A30ZA)
<b>VAC VOLTAGE AVAILABLE</b>	120 / 240	<b>BATTERY</b>	N/A
<b>MAXIMUM CONTINUOUS AC OUTPUT (WATTS)</b>	5500	<b>APPROXIMATE RUNNING TIME / TANKFUL (HRS.)</b>	7.1** / 10.0****
<b>MAX. RATED AC AMPERAGE @ 120 V / 240 V</b>	45.8 / 22.9	<b>RATED FUEL CONSUMPTION (LITRES / HOUR)</b>	3.38**
<b>GROUND FAULT CIRCUIT INTERRUPTER (GFCI)</b>	-	<b>NOISE LEVEL (DBA) (1.5 METRES TO 7 METRES)</b>	74**
<b>FREQUENCY (HERTZ)</b>	60	<b>LENGTH (WITHOUT HANDLES AND WHEELS)</b>	681 mm (26.8 in.)
<b>AUTOMATIC VOLTAGE REGULATOR</b>	STD. DIGITAL (DAVR)	<b>LENGTH (WITH HANDLES AND WHEELS)</b>	-
<b>DC OUTPUT (VOLTS / AMPS)</b>	-	<b>WIDTH (WITHOUT HANDLES AND WHEELS)</b>	530 mm (20.9 in.)
<b>ENGINE TYPE</b>	Honda GX390T2, OHV, 4-STROKE, AIR-COOLED	<b>WIDTH (WITH HANDLES AND WHEELS)</b>	-
<b>DISPLACEMENT</b>	389 cc	<b>HEIGHT (WITHOUT LIFT-HOOK)</b>	571 mm (22.5 in.)
<b>STARTING SYSTEM</b>	MANUAL RECOIL	<b>HEIGHT (WITH LIFT-HOOK)</b>	-
<b>LOW LEVEL OIL ALERT™ SYSTEM</b>	STD.	<b>DRY WEIGHT</b>	80 kg (176.4 lb)
<b>AUTO THROTTLE</b>	-	<b>COLD CLIMATE TECHNOLOGY</b>	STD.
<b>REMOTE START CAPABILITY</b>	NO	<b>COMMON DUPLEX RECEPTACLE SPECIFICATIONS</b>	40 amps / 120 VAC continuous is available as combined total from these two AC receptacles. Maximum of 20 amps available from each single receptacle.
<b>REMOTE START KIT PART NUMBER INFO</b>	-	<b>DC RECEPTACLE SPECIFICATIONS</b>	-
<b>FUEL TANK CAPACITY (LITRES)</b>	24	<b>DC CHARGING CABLE</b>	N/A
		<b>HIGH CAPACITY 120/240 AC TWIST LOCK RECEPTACLE SPECS</b>	This receptacle will supply 30 amps at 120 VAC continuously. This receptacle will supply 22.9 amps at 240 VAC continuously and 45.8 amps at 120 VAC.

Models and/or colours may not be exactly as shown. Errors and omissions excepted. Specifications are subject to change without notice. See your Honda Power Equipment dealer for details.

For optimum performance and safety, please read your owner's manual before operating your Honda product. Always wear the appropriate safety gear when operating your Honda.

®/TM — Trademarks of Honda Canada Inc. or used under licence from Honda Motor Co., Ltd. or third parties.